FUJITSU SEMICONDUCTOR
DATA SHEET

DS501-00003-1v0-E

Memory FRAM

1 M Bit (128 K × 8)

MB85R1001A

■ DESCRIPTIONS

The MB85R1001A is an FRAM (Ferroelectric Random Access Memory) chip consisting of 131,072 words × 8 bits of nonvolatile memory cells fabricated using ferroelectric process and silicon gate CMOS process technologies.

The MB85R1001A is able to retain data without using a back-up battery, as is needed for SRAM.

The memory cells used in the MB85R1001A can be used for 10^{10} read/write operations, which is a significant improvement over the number of read and write operations supported by Flash memory and E^2PROM.

The MB85R1001A uses a pseudo-SRAM interface that is compatible with conventional asynchronous SRAM.

■ FEATURES


- Bit configuration : 131,072 words × 8 bits
- Read/write endurance : 10^{10} times
- Operating power supply voltage : 3.0 V to 3.6 V
- Operating temperature range : − 40 °C to + 85 °C
- Data retention : 10 years (+ 55 °C)
- Package : 48-pin plastic TSOP (1)

Copyright©2011 FUJITSU SEMICONDUCTOR LIMITED All rights reserved

深圳市满度科技有限公司
Web:www.manduic.com
Tel:150-1290-5940
Email:sales@manduic.com
微信扫码咨询客服

■ PIN ASSIGNMENTS

(TOP VIEW)




(FPT-48P-M48)

■ PIN DESCRIPTIONS

Pin Number	Pin Name	Functional Description
1, 2, 4, 5, 8, 18 to 26, 28, 29, 45	A0 to A16	Address Input pins
33 to 35, 38 to 42	I/O1 to I/O8	Data Input/Output pins
44	$\overline{CE}$1	Chip Enable 1 Input pin
7	CE2	Chip Enable 2 Input pin
6	$\overline{WE}$	Write Enable Input pin
48	$\overline{OE}$	Output Enable Input pin
10, 16, 37	VDD	Supply Voltage pins Connect all three pins to the power supply.
13, 27, 46	VSS	Ground pins Connect all three pins to ground.
3, 9, 11, 12, 14, 15, 17, 30 to 32, 36, 43, 47	NC	No Connect pins

深圳市满度科技有限公司
Web:www.manduic.com
Tel:136-1290-5940
Email:sales@manduic.com

■ BLOCK DIAGRAM



■ FUNCTIONAL TRUTH TABLE

Operation Mode	$\overline{CE}1$	CE2	$\overline{WE}$	$\overline{OE}$	I/O1 to I/O8	Supply Current
Standby Precharge	H	X	X	X	Hi-Z	Standby (I_{SB})
	X	L	X	X		
	X	X	H	H		
Read	↓	H	H	L	Data Output	Operation (I_{CC})
	L	↑				
Read (Pseudo-SRAM, $\overline{OE}$ control*1)	L	H	H	↓		
Write	↓	H	L	H	Data Input	
	L	↑				
Write (Pseudo-SRAM, $\overline{WE}$ control*2)	L	H	↓	H		

Note: L = V_{IL}, H = V_{IH}, X can be either V_{IL} or V_{IH}, Hi-Z = High Impedance

↓ : Latch address and latch data at falling edge, ↑ : Latch address and latch data at rising edge

*1 : $\overline{OE}$ control of the Pseudo-SRAM means the valid address at the falling edge of $\overline{OE}$ to read.

*2 : $\overline{WE}$ control of the Pseudo-SRAM means the valid address and data at the falling edge of $\overline{WE}$ to write.

深圳市满度科技有限公司
Web:www.manduic.com
Tel:159-1290-5940
Email:sales@manduic.com

■ ABSOLUTE MAXIMUM RATINGS

Parameter	Symbol	Rating		Unit
		Min	Max	
Power Supply Voltage*	V_{CC}	– 0.5	+ 4.0	V
Input Pin Voltage*	V_{IN}	– 0.5	V_{CC} + 0.5 (≤ 4.0)	V
Output Pin Voltage*	V_{OUT}	– 0.5	V_{CC} + 0.5 (≤ 4.0)	V
Operating Temperature	T_A	– 40	+ 85	°C
Storage Temperature	T_{STG}	– 40	+ 125	°C

* : All voltages are referenced to VSS = 0 V.

WARNING: Semiconductor devices can be permanently damaged by application of stress (voltage, current, temperature, etc.) in excess of absolute maximum ratings. Do not exceed these ratings.

■ RECOMMENDED OPERATING CONDITIONS

Parameter	Symbol	Value			Unit
		Min	Typ	Max	
Power Supply Voltage*	V_{CC}	3.0	3.3	3.6	V
High Level Input Voltage*	V_{IH}	$V_{CC} \times 0.8$	—	V_{CC} + 0.5(≤ 4.0)	V
Low Level Input Voltage*	V_{IL}	– 0.5	—	+ 0.6	V
Operating Temperature	T_A	– 40	—	+ 85	°C

* : All voltages are referenced to VSS = 0 V.

WARNING: The recommended operating conditions are required in order to ensure the normal operation of the semiconductor device. All of the device's electrical characteristics are warranted when the device is operated within these ranges.

Always use semiconductor devices within their recommended operating condition ranges. Operation outside these ranges may adversely affect reliability and could result in device failure.

No warranty is made with respect to uses, operating conditions, or combinations not represented on the data sheet. Users considering application outside the listed conditions are advised to contact their representatives beforehand.

深圳市满度科技有限公司
Web:www.manduic.com
Tel:138-1290-5940
Email:sales@manduic.com

■ ELECTRICAL CHARACTERISTICS

1. DC Characteristics

(within recommended operating conditions)

Parameter	Symbol	Condition	Value			Unit
			Min	Typ	Max	
Input Leakage Current	$\|I_{LI}\|$	V_{IN} = 0 V to V_{CC}	—	—	10	µA
Output Leakage Current	$\|I_{LO}\|$	V_{OUT} = 0 V to V_{CC}, $\overline{CE}1 = V_{IH}$ or $\overline{OE} = V_{IH}$	—	—	10	µA
Operating Power Supply Current	I_{CC}	$\overline{CE}1$ = 0.2 V, CE2 = V_{CC}–0.2 V, I_{out} = 0 mA*1	—	10	15	mA
Standby Current	I_{SB}	$\overline{CE}1 \geq V_{CC}$–0.2 V CE2 ≤ 0.2 V*2 $\overline{OE} \geq V_{CC}$–0.2 V, $\overline{WE} \geq V_{CC}$–0.2 V*2	—	10	50	µA
High Level Output Voltage	V_{OH}	I_{OH} = –1.0 mA	$V_{CC} \times 0.8$	—	—	V
Low Level Output Voltage	V_{OL}	I_{OL} = 2.0 mA	—	—	0.4	V

*1 : During the measurement of I_{CC}, the Address, Data In were taken to only change once per active cycle.
I_{out}: output current

*2 : All pins other than setting pins should be input at the CMOS level voltages such as H ≥ V_{CC} – 0.2 V, L ≤ 0.2 V.

深圳市满度科技有限公司 Tel:159-1290-5940
Web:www.manduic.com Email:sales@manduic.com

2. AC Characteristics

• **AC Test Conditions**

Supply Voltage	: 3.0 V to 3.6 V
Operating Temperature	: –40 °C to +85 °C
Input Voltage Amplitude	: 0.3 V to 2.7 V
Input Rising Time	: 5 ns
Input Falling Time	: 5 ns
Input Evaluation Level	: 2.0 V / 0.8 V
Output Evaluation Level	: 2.0 V / 0.8 V
Output Impedance	: 50 pF

(1) Read Cycle

(within recommended operating conditions)

Parameter	Symbol	Value		Unit
		Min	Max	
Read Cycle Time	t_{RC}	150	—	ns
$\overline{CE}$1 Active Time	t_{CA1}	120	—	ns
CE2 Active Time	t_{CA2}	120	—	ns
$\overline{OE}$ Active Time	t_{RP}	120	—	ns
Precharge Time	t_{PC}	20	—	ns
Address Setup Time	t_{AS}	0	—	ns
Address Hold Time	t_{AH}	50	—	ns
$\overline{OE}$ Setup Time	t_{ES}	0	—	ns
Output Hold Time	t_{OH}	0	—	ns
Output Set Time	t_{LZ}	30	—	ns
$\overline{CE}$1 Access Time	t_{CE1}	—	100	ns
CE2 Access Time	t_{CE2}	—	100	ns
$\overline{OE}$ Access Time	t_{OE}	—	100	ns
Output Floating Time	t_{OHZ}	—	20	ns

(2) Write Cycle

(within recommended operating conditions)

Parameter	Symbol	Value		Unit
		Min	Max	
Write Cycle Time	t_{WC}	150	—	ns
$\overline{CE}$1 Active Time	t_{CA1}	120	—	ns
CE2 Active Time	t_{CA2}	120	—	ns
Precharge Time	t_{PC}	20	—	ns
Address Setup Time	t_{AS}	0	—	ns
Address Hold Time	t_{AH}	50	—	ns
Write Pulse Width	t_{WP}	120	—	ns
Data Setup Time	t_{DS}	0	—	ns
Data Hold Time	t_{DH}	50	—	ns
Write Setup Time	t_{WS}	0	—	ns

深圳市满度科技有限公司
Web:www.manduic.com
Tel:138-1290-5940
Email:sales@manduic.com


3. Pin Capacitance

Parameter	Symbol	Condition	Value			Unit
			Min	Typ	Max	
Input Capacitance	C_{IN}	$V_{IN} = V_{OUT} = 0$ V, f = 1 MHz, T_A = +25 °C	—	—	10	pF
Output Capacitance	C_{OUT}		—	—	10	pF


深圳市满度科技有限公司
Web:www.manduic.com
Tel:150-1290-5940
Email:sales@manduic.com

■ TIMING DIAGRAMS

1. Read Cycle Timing ($\overline{CE}$1, CE2 Control)




2. Read Cycle Timing ($\overline{OE}$ Control)




深圳市满度科技有限公司
Web:www.manduic.com
Tel:136-1290-5940
Email:sales@manduic.com

3. Write Cycle Timing ($\overline{CE}$1, CE2 Control)




4. Write Cycle Timing ($\overline{WE}$ Control)



深圳市满度科技有限公司
Web:www.manduic.com
Tel:159-1290-5940
Email:sales@manduic.com

■ POWER ON/OFF SEQUENCE



* : $\overline{CE}1$ (Max) < V_{CC} + 0.5 V

Notes: • Use either of $\overline{CE}1$ or CE2, or both for disable control of the device.

- Because turning the power-on from an intermediate level cause malfunction, when the power is turned on, V_{CC} is required to be started from 0 V.
- If the device does not operate within the specified conditions of read cycle, write cycle, power on/off sequence, memory data can not be guaranteed.
- When turning the power on or off, it is recommended that CE2 is connected to ground to prevent unexpected writing.

(within recommended operating conditions)

Parameter	Symbol	Value			Unit
		Min	Typ	Max	
$\overline{CE}1$ level hold time for Power OFF	t_{PD}	85	—	—	ns
$\overline{CE}1$ level hold time for Power ON	t_{PU}	85	—	—	ns
Power supply rising time	t_R	0.05	—	200	ms

■ NOTES ON USE

After the IR reflow completed, it is not guaranteed to hold the data written prior to the IR reflow.


深圳市满度科技有限公司
Web:www.manduic.com
Tel:138-1290-5940
Email:sales@manduic.com

■ ORDERING INFOMATION

Part Number	Package
MB85R1001ANC-GE1	48-pin plastic TSOP(1) (FPT-48P-M48)


深圳市满度科技有限公司
Web:www.manduic.com
Tel:150-1290-5940
Email:sales@manduic.com

■ PACKAGE DIMENSIONS

48-pin plastic TSOP		
	Lead pitch	0.50 mm
	Package width × package length	12.00 mm × 12.40 mm
	Lead shape	Gullwing
	Sealing method	Plastic mold
	Mounting height	1.20 mm MAX
	Weight	0.36 g
(FPT-48P-M48)		

48-pin plastic TSOP
(FPT-48P-M48)

Note 1) # : Resin protrusion. (Each side : +0.15 (.006) Max).
Note 2) * : These dimensions do not include resin protrusion.
Note 3) Pins width and pins thickness include plating thickness.
Note 4) Pins width do not include tie bar cutting remainder.



© 2010 FUJITSU SEMICONDUCTOR LIMITED F48048Sc-1-1

Dimensions in mm (inches).
Note: The values in parentheses are reference values.

Please check the latest package dimension at the following URL.
http://edevice.fujitsu.com/package/en-search/

深圳市满度科技有限公司
Web:www.manduic.com
Tel:139-1290-5940
Email:sales@manduic.com

MEMO

深圳市满度科技有限公司
Web:www.manduic.com
Tel:158-1290-5940
Email:sales@manduic.com

MEMO

深圳市满度科技有限公司
Web:www.manduic.com
Tel:139-1290-5940
Email:sales@manduic.com

MEMO

深圳市满度科技有限公司
Web:www.manduic.com
Tel:159-1290-5940
Email:sales@manduic.com

FUJITSU SEMICONDUCTOR LIMITED

Nomura Fudosan Shin-yokohama Bldg. 10-23, Shin-yokohama 2-Chome,
Kohoku-ku Yokohama Kanagawa 222-0033, Japan
Tel: +81-45-415-5858
http://jp.fujitsu.com/fsl/en/

For further information please contact:

North and South America
FUJITSU SEMICONDUCTOR AMERICA, INC.
1250 E. Arques Avenue, M/S 333
Sunnyvale, CA 94085-5401, U.S.A.
Tel: +1-408-737-5600 Fax: +1-408-737-5999
http://us.fujitsu.com/micro/

Europe
FUJITSU SEMICONDUCTOR EUROPE GmbH
Pittlerstrasse 47, 63225 Langen, Germany
Tel: +49-6103-690-0 Fax: +49-6103-690-122
http://emea.fujitsu.com/semiconductor/

Korea
FUJITSU SEMICONDUCTOR KOREA LTD.
902 Kosmo Tower Building, 1002 Daechi-Dong,
Gangnam-Gu, Seoul 135-280, Republic of Korea
Tel: +82-2-3484-7100 Fax: +82-2-3484-7111
http://kr.fujitsu.com/fsk/

Asia Pacific
FUJITSU SEMICONDUCTOR ASIA PTE. LTD.
151 Lorong Chuan,
#05-08 New Tech Park 556741 Singapore
Tel : +65-6281-0770 Fax : +65-6281-0220
http://sg.fujitsu.com/semiconductor/

FUJITSU SEMICONDUCTOR SHANGHAI CO., LTD.
Rm. 3102, Bund Center, No.222 Yan An Road (E),
Shanghai 200002, China
Tel : +86-21-6146-3688 Fax : +86-21-6335-1605
http://cn.fujitsu.com/fss/

FUJITSU SEMICONDUCTOR PACIFIC ASIA LTD.
10/F., World Commerce Centre, 11 Canton Road,
Tsimshatsui, Kowloon, Hong Kong
Tel : +852-2377-0226 Fax : +852-2376-3269
http://cn.fujitsu.com/fsp/

Specifications are subject to change without notice. For further information please contact each office.

All Rights Reserved.
The contents of this document are subject to change without notice.
Customers are advised to consult with sales representatives before ordering.
The information, such as descriptions of function and application circuit examples, in this document are presented solely for the purpose of reference to show examples of operations and uses of FUJITSU SEMICONDUCTOR device; FUJITSU SEMICONDUCTOR does not warrant proper operation of the device with respect to use based on such information. When you develop equipment incorporating the device based on such information, you must assume any responsibility arising out of such use of the information.
FUJITSU SEMICONDUCTOR assumes no liability for any damages whatsoever arising out of the use of the information.
Any information in this document, including descriptions of function and schematic diagrams, shall not be construed as license of the use or exercise of any intellectual property right, such as patent right or copyright, or any other right of FUJITSU SEMICONDUCTOR or any third party or does FUJITSU SEMICONDUCTOR warrant non-infringement of any third-party's intellectual property right or other right by using such information. FUJITSU SEMICONDUCTOR assumes no liability for any infringement of the intellectual property rights or other rights of third parties which would result from the use of information contained herein.
The products described in this document are designed, developed and manufactured as contemplated for general use, including without limitation, ordinary industrial use, general office use, personal use, and household use, but are not designed, developed and manufactured as contemplated (1) for use accompanying fatal risks or dangers that, unless extremely high safety is secured, could have a serious effect to the public, and could lead directly to death, personal injury, severe physical damage or other loss (i.e., nuclear reaction control in nuclear facility, aircraft flight control, air traffic control, mass transport control, medical life support system, missile launch control in weapon system), or (2) for use requiring extremely high reliability (i.e., submersible repeater and artificial satellite).
Please note that FUJITSU SEMICONDUCTOR will not be liable against you and/or any third party for any claims or damages arising in connection with above-mentioned uses of the products.
Any semiconductor devices have an inherent chance of failure. You must protect against injury, damage or loss from such failures by incorporating safety design measures into your facility and equipment such as redundancy, fire protection, and prevention of over-current levels and other abnormal operating conditions.
Exportation/release of any products described in this document may require necessary procedures in accordance with the regulations of the Foreign Exchange and Foreign Trade Control Law of Japan and/or US export control laws.
The company names and brand names herein are the trademarks or registered trademarks of their respective owners.

Edited: Sales Promotion Department

深圳市满度科技有限公司
Web:www.manduic.com
Tel:150-1290-5940
Email:sales@manduic.com